

S2053 多功能校验仪 Multifunctional Calibrator

- 可以输出电压、电流、电阻、24V 电源，同时测量电压、电流、电阻信号
Output voltage, current, resistance, 24V loop power, and measure voltage, current, resistance signals at the same time.
- 采用数字信号源、轻触键盘和大屏幕液晶显示器，输出和测量数据同时显示
Adopt digital signal source, touch keyboard and large-screen LCD display.



产品特点 Product Features

- 输出、测量、24V 电源相互隔离，互不干扰 Independent source, measurement, loop power supply functions
- 高性能数字信号源，稳定可靠 Reliable high-performance digital signal source
- 可设定输出范围，具有阶跃输出功能 Settable output range with step output function
- 大屏幕显示器，同时显示输出和测量 Large screen to display output and measurement simultaneously
- 全功能自我保护，有效克服误操作 Full-function self-protection to effectively overcome misuse
- 两种配置选择：一路测量一路输出型和一路测量两路输出型 Two configuration options: one measurement and one output; one measurement two outputs

主要技术指标 Main Specifications

功能 Function	输出 Output	测量 Measurement
mV	0-110.000 mV	0-380.00 mV
V	0-11.0000 V	0-38.000 V
mA	0-25.000 mA	0-38.000 mA
Ω	0-2200.0 Ω	0-3800.0 Ω
精度 Accuracy	0.02% - 0.03%	0.03% - 0.04%
24V 电源 Loop power	24V/0.5A	-
供电电源 Power supply : AC220V $\pm$ 10%, 50Hz $\pm$ 5%, 外形尺寸 Dimensions : 300 $\times$ 100 $\times$ 280 (mm) , 重量 Weight : 3kg		